

# Battery Unit Capacity Chart

## BATTERY UNIT

|            | WATTAGE CAPACITY |      |      |      |      |
|------------|------------------|------|------|------|------|
|            | 30MIN            | 1H00 | 1H30 | 2H00 | 4H00 |
| 6V - 36W   | 36               | 21   | 15   | 12   | 6    |
| 6V - 72W   | 72               | 42   | 30   | 24   | 12   |
| 6V - 108W  | 108              | 63   | 45   | 36   | 18   |
| 6V - 180W  | 180              | 105  | 75   | 60   | 30   |
| 12V - 36W  | 36               | 21   | 15   | 12   | 6    |
| 12V - 72W  | 72               | 42   | 30   | 24   | 12   |
| 12V - 100W | 100              | 58   | 42   | 33   | 17   |
| 12V - 144W | 144              | 84   | 60   | 48   | 24   |
| 12V - 200W | 200              | 117  | 83   | 67   | 33   |
| 12V - 250W | 250              | 144  | 100  | 83   | 42   |
| 12V - 288W | 288              | 168  | 120  | 96   | 48   |
| 12V - 360W | 360              | 210  | 150  | 120  | 60   |
| 24V - 144W | 144              | 84   | 60   | 48   | 24   |
| 24V - 200W | 200              | 117  | 83   | 67   | 33   |
| 24V - 288W | 288              | 168  | 120  | 96   | 48   |
| 24V - 350W | 350              | 200  | 144  | 120  | 60   |
| 24V - 432W | 432              | 250  | 180  | 144  | 72   |
| 24V - 550W | 550              | 320  | 230  | 180  | 90   |



**RGS**



**RGS-TB**



**PHANTOM**



**Q-BIC  
RG-QB**